

AVG-10G

GSM Gate Control

How it works? When you call the **AVG-10G** number the system check if your number is listed, if positive the **AVG10G** activates a relay that trig the gate opening mechanism, it's a free call as the unit doesn't answer. No more lost or fail radio remote!
Very low maintaining costs for residential and large parking lots
Provides remote opening for visitors and associates



Main features

- Supports up to 2000 accounts stored in electronic flash memory
- Special numbers (400) schedule authorization time and days
- Model AVG-10GS send SMS notification for each gate open (SW required)
- Slim size enables fitting in small space cabinets
- Programming by SMS or Excel files import, SMS confirmation during program mode
- Log (2000 events) report and remote programming via PC and serial cable or with GSM modem (not included), simplifies update and memory list
- Relay output for gate or door activation (1A@30V. Com & N.O.)
- Powered by the gate power supply or simple wall plug 12V DC 1.5A adapter
- Features and phone numbers entered by SMS or PC (requires the AVG10_GSW pack)
- Simple installation, easy attaching to wall or DIN rail
- Quad band: GSM 850/900/1800/1900MHz
- Operating temperature: -20°C to +60°C
- Dimensions: 98 x 82 x 30 mm
- Kit contains interface wires and antenna

